

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA

AMENDMENTS

In the Specification:

The entire specification has amended for editorial and typographical errors. A substituted specification, in both a marked up version and a clean version, are enclosed.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 **POWER AMPLIFIER WITH ACTIVE BIAS CIRCUIT**

CROSS-REFERENCE TO RELATED APPLICATION

This application claims the priority benefit of Taiwan application serial no.

10 92128662, filed on October 16, 2003.

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] The present invention relates to a power amplifier. More particularly, the
15 present invention relates to a power amplifier with an active bias circuit for improving
power-added efficiency (PAE).

Description of Related Art

[0002] A power amplifier (PA) is an important device in the microwave circuits.
20 For example, a power amplifier is used to amplify the broadcast signals at the
transmission (TX) terminal of a radio frequency circuit. With the popularity of
portable communication systems, a maximum output power and output power
efficiency have become critical factors for the development of the wireless transmission.

[0003] The output efficiency of the power amplifier is represented by the output
25 power and the output power efficiency. Typically, the maximum output power is the
most important factor in output power while a power gain and power-added efficiency
(PAE) are the two most important factors in output power efficiency. The power gain
of the amplifier is defined as a ratio of the output power to an input power. In other

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 words, a larger power gain implies a higher amplifying capacity for the power amplifier.

The power-added efficiency is an ability that the power amplifier converts a direct current (DC) input power into an alternating current (AC) output power. In fact, power-added efficiency is defined as the ratio of the direct current (DC) input power to the alternating current (AC) output power, or $PAE = (AC \text{ output power} - DC \text{ input power}) / DC \text{ input power}$.

10 Similarly, the higher the power-added efficiency, the better the power amplifier is. FIG. 1 is a graph showing the relationship of the output power, the power gain and the power-added efficiency versus the input power of a conventional power amplifier. As shown in FIG. 1, most power amplifiers have excellent output power linearity when the input power is small. However, when the input power is

15 large, the output power is no longer linearly amplified and results in a drop in the gain. This drop in the gain is known as a gain compression. The quality of the power amplifier can be assessed according to the input power at which the gain compression is generated because a later generation of the gain compression means that the power amplifier has better output linearity and maintains a distortion free signal output for a

20 larger input power range.

[0004] FIG. 2 is a circuit diagram of a conventional semiconductor transistor power amplifier. As shown in FIG. 2, the transistor 202 serves as a power amplifier transistor and may be such as a CMOS transistor. In FIG. 2, V_g is the gate bias voltage for the transistor 202; P_{in} is the input power; P_{out} is the output power. In a

25 conventional CMOS power amplifier, a class-A bias design is often adopted. In the class-A bias design, the transistor 202 is biased at a half of the saturation voltage V_{sat} thereof so that a full wave transmission of signal is still possible at a larger output power level. Hence, the power amplifier can have a higher output power and a higher

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 power gain as well as a distortion free linear operating region. However, a
disadvantage is that most A-class power amplifiers are designed to use a single constant
gate bias voltage (for example, the gate bias voltage V_g of the transistor 202 is still at
half V_{dd}). Since output power is equal to a product of voltage and current, power
consumption is only reduced by a little at a low output power when the current flow is
10 small and hence leads to an undesirable waste of DC power.

[0005] Therefore, in order to increase output the power efficiency of the power
amplifier, the power amplifier sometimes operates in a class-AB or class-B operating
region. In other words, the gate bias voltage V_g of the transistor 202 in FIG. 2 is
lowered. Thus, the power-added efficiency (PAE) of the power amplifier is increased.
15 However, the signal waveform is constrained by the gate bias voltage when the output
power is large so that the maximum output power and linearity of the power amplifier
are reduced.

[0006] Hence, enhancing the power-added efficiency and lower direct current
power consumption of a the power amplifier without reducing the maximum output
20 power and linearity of operation of the device is important and required.

SUMMARY OF THE INVENTION

[0007] Accordingly, at least one objective of the present invention is to provide a
power amplifier with an active bias circuit capable of increasing the power-added
25 efficiency of the amplifier so that a direct current (DC) power consumption is reduced
without reducing a maximum output power or decreasing linearity of the output power.

[0008] To achieve these and other advantages and in accordance with the purpose
of the invention, as embodied and broadly described herein, the invention provides a

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 power amplifier with an active bias circuit. The power amplifier includes a power amplifier transistor and the active bias circuit. The power amplifier transistor has the gate connected to a gate bias voltage. The active bias circuit is connected to an input power terminal and the gate of the power amplifier transistor for receiving an input power from the input power terminal and applying a bias voltage to the gate of the
10 power amplifier transistor. Hence, the gate bias voltage will increase in accordance with an increase of the input power.

[0009] In the aforementioned power amplifier, the curve of an increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

[0010] Preferably, the power amplifier transistor and the active bias circuit is
15 manufactured by a system on chip (SOC) process.

[0011] Preferably, the active bias circuit of the aforementioned power amplifier includes a diode and a resistor, and an equivalent resistance of the diode varies corresponding to the input power.

[0012] This invention also provides an integrated circuit for a power amplifier
20 with an active bias circuit. The integrated circuit includes a power output device, a power amplifier transistor, an active bias circuit and a power input device. The power amplifier transistor has a gate connected to a gate bias voltage. The active bias circuit is connected to the power output device and the gate of the power amplifier transistor for receiving input power from the power output device and applying a bias voltage to
25 the gate of the power amplifier transistor. Hence, the gate bias voltage will increase in accordance with an increase of the input power. The power input device is connected to an output terminal of the power amplifier transistor for receiving the amplified output from the power amplifier transistor.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 [0013] In the aforementioned integrated circuit, the curve of the increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

 [0014] Preferably, the power amplifier transistor and the active bias circuit is manufactured by a system on chip (SOC) process.

 [0015] Preferably, the active bias circuit of the aforementioned integrated circuit
10 includes a diode and a resistor, and the equivalent resistance of the diode varies corresponding to the input power.

 [0016] This invention also provides a method of providing a gate bias voltage to a transistor power amplifier according to the input power. The method includes providing an input power and then outputting a gate bias voltage corresponding to the
15 input power wherein the gate bias voltage is increased in accordance with the input power.

 [0017] In the aforementioned method, the curve of the increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

 [0018] Accordingly, the power amplifier of the invention can provide a lower
20 gate bias voltage (close to the operating range of a conventional class-AB or class B power amplifier) when the input power is low, and a higher gate bias voltage (close to the operating range of a conventional class-A power amplifier) when the input power is high. Therefore, the power amplifier of this invention has a high output power and linearity of operation as well as a high power-added efficiency regardless of whether the
25 input power is low or high.

 [0019] It is to be understood that both the foregoing general description and the following detailed description are exemplary, and are intended to provide further explanation of the invention as claimed.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5

BRIEF DESCRIPTION OF THE DRAWINGS

[0020] The accompanying drawings are included to provide a further understanding of the invention, and are incorporated in and constitute a part of this specification. The drawings illustrate embodiments of the invention and, together with
10 the description, serve to explain the principles of the invention.

[0021] FIG. 1 is a graph showing the relationships of output power, power gain and power-added efficiency versus input power of a conventional power amplifier.

[0022] FIG. 2 is a circuit diagram of a conventional semiconductor transistor power amplifier.

15 [0023] FIG. 3 is a circuit diagram of a power amplifier with an active bias circuit according to one embodiment of this invention.

[0024] FIG. 4 is a graph showing the relationship of the equivalent resistance versus the input power of a diode.

20 [0025] FIG. 5 is a graph showing the relationship of the gate bias voltage versus the input power for a power amplifier with active bias circuit of the invention and a conventional A-class power amplifier.

[0026] FIG. 6 is a graph showing the relationships of output power, power gain and power-added efficiency versus input power for a power amplifier with active bias circuit according to this invention and the similar relationships of a conventional
25 class-A power amplifier.

[0027] FIG. 7 is a circuit diagram of a CMOS power amplifier with an active bias circuit according to one embodiment of this invention.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 [0028] FIG. 8 is a graph showing the relationship of the output current versus the gate bias voltage of the two transistor circuits inside the active bias circuit according to one embodiment of this invention.

 [0029] FIG. 9 is a graph showing the relationship of the drain-to-source current versus the input power of a power amplifier with an active bias circuit according to this
10 invention and a conventional A-class power amplifier.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

 [0030] Reference will now be made in detail to the present embodiments of the invention, examples of which are illustrated in the accompanying drawings. Wherever
15 possible, the same reference numbers are used in the drawings and the description to refer to the same or like elements.

 [0031] FIG. 3 is a circuit diagram of a power amplifier with an active bias circuit according to one embodiment of this invention. As shown in FIG. 3, the power amplifier 300 comprises a transistor 302 and an active bias circuit 304. The transistor
20 302 serves as a power amplifier transistor such as a CMOS transistor. V_{g1} is a gate bias voltage applied to the transistor 302. P_{in} is an input power and P_{out} is an output power. The active bias circuit 304 further comprises a diode 306 and a resistor 308. FIG. 4 is a graph showing the relationship of an equivalent resistance versus the input power of the diode. As shown in FIG. 4, when a signal with a definite power passes
25 through a parallel connected diode, the equivalent resistance of the diode will decrease with an increase in the signal power regardless of whether the diode is set in forward or reverse bias. Hence, if the input power P_{in} of the active bias circuit 304 in FIG. 3 is low, the active bias circuit 304 is equivalent to a voltage divider constructed by a

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 forward bias diode and a serially connected and grounded resistor with high resistance.

Thus, by adjusting the resistance of the resistor, the transistor 302 can be operated at a lower gate bias voltage V_{g1} (that is, the gate bias voltage V_{g1} is in the conventional class-AB or class-B operating range). In other words, when the input power P_{in} is low, the power amplifier 300 with the active bias circuit is able to provide a higher

10 power-added efficiency (PAE) so that the DC power consumption is reduced.

[0032] On the other hand, when the input power P_{in} in FIG. 3 is increased, the equivalent resistance of the diode 306 is reduced so that the voltage across the resistor 308 is increased. Consequently, with an increase of the input power P_{in} , the gate bias voltage V_{g1} applied to the transistor 302 is also increased (that is, the gate bias voltage

15 V_{g1} is in the conventional class-A operating range). In other words, the power amplifier 300 with the active bias circuit is able to provide a higher output power and an excellent linearity of the output power similar to a conventional class-A power amplifier.

[0033] FIG. 5 is a graph showing the relationship of the gate bias voltage V_{g1} applied to the transistor 302 of the power amplifier 300 in FIG. 3 and the gate bias voltage V_g applied to the transistor of a conventional A-class power amplifier versus the input power. As shown in FIG. 5, the conventional A-class power amplifier always has an almost constant gate bias voltage value regardless of whether the input power is high or low. In the power amplifier of this invention, the gate bias voltage value is low
25 when the input power is low and the gate bias voltage value is high when the input power is high.

[0034] FIG. 6 is a graph showing the relationship of the output power, power gain and power-added efficiency versus the input power for the power amplifier with the

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 active bias circuit according to this invention and the similar relationships of a
conventional class-A power amplifier. As shown in FIG. 6, the power amplifier
according to this invention has a higher power-added efficiency than a conventional
class-A power amplifier since as shown in FIG. 5, the gate bias voltage of a
conventional A-class power amplifier is almost constant and the gate bias voltage of the
10 power amplifier of this invention is dependent on the input power. Thus, when the
input power is low, the power amplifier has a low gate bias voltage (close to the
operating range of a conventional class-AB or a class-B amplifier). Conversely, when
the input power is high, the power amplifier has a high gate bias voltage (close to the
operating range of a conventional class-A amplifier). In other words, the power
15 amplifier of this invention is able to provide both high output power and excellent
linearity as a conventional class-A amplifier and to provide a high power-added
efficiency as a conventional class-AB or class-B amplifier.

[0035] FIG. 7 is a circuit diagram of a CMOS power amplifier with an active bias
circuit according to one embodiment of this invention. As shown in FIG. 7, the
20 CMOS power amplifier 700 comprises a transistor 702, an active bias circuit 704 and
other circuits including inductors and capacitors for impedance matching. The
transistor 702 is a major component serving as a power-amplifying transistor in the
power amplifier 700. The active bias circuit 704 is a circuit for providing the
transistor 702 with a gate bias voltage V_{gb1} . The inductors and capacitors together
25 form an impedance matching network.

[0036] Inside the active bias circuit 704, a transistor 712 functions as a diode and
resistors 714, 716 serve to adjust the gate bias voltage and set the basic level of the gate
bias voltage curve as well as provide a cutter for high frequency signals. A depletion

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 transistor 718 functions as a diode and connects serially with a resistor 720. Although the equivalent resistance of the transistor 718 will vary corresponding to the power of the signal, however, the overall effect of the transistor 718 and the resistor 720 is to adjust the basic level of the gate bias voltage because the resistance of the resistor 720 is substantially higher than those of the resistor 714 and 716.

10 [0037] FIG. 8 is a graph showing the relationship of the output current versus the gate bias voltage for two transistor circuits inside the active bias circuit shown in FIG. 7. As shown in FIG. 8, the curves of the output current for the transistor 712 versus the gate bias voltage V_{gb1} is represented by a plurality of curves L1 with a scale labeled on the right vertical axis. Similarly, the curve of the output current for the transistor 718
15 versus the gate bias voltage V_{gb1} is represented by a curve L2 with a scale labeled on the left vertical axis. In FIG. 8, the L1 curves show the output current of the gate bias voltage V_{gb1} for four different input power levels (e.g., input power of -20dBm, -10dBm, 0dBm and 5dBm respectively). It is noted that the gate bias voltage V_{gb1} increases with an increase of the input power. Furthermore, the gate bias voltage V_{gb1}
20 of the cross points of the left curve L2 and the right curves L1 is the gate bias voltage V_{gb1} applied to the power-amplifying transistor 702. Therefore, the gate bias voltage V_{gb1} applied to the transistor 702 increases when the input power is increased.

[0038] FIG. 9 is a graph showing the relationship of a drain-to-source current versus the input power for a power amplifier with an active bias circuit according to this
25 invention and a conventional A-class power amplifier. A conventional A-class power amplifier always has an almost constant gate bias voltage regardless of whether the input power is high or low. Therefore, the effect of input power on the drain-to-source current is minimal. In the power amplifier of this invention, the gate bias voltage is

5 low when the input

Conversely, the gate
drain-to-source current
voltage, the power is
relatively high power

10 input power is low.

similar to a conventional
higher output power

[0039] In another

active bias circuit method

15 an SOC product, the

devices are very important
deeper N-type doped

[0040] According to

gate bias voltage (clock

20 power amplifier) when

the operating range is

high. Therefore, the

linearity of operation

input power is low or

25 [0041] It will be

variations can be made

the scope or spirit of

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 active bias circuit according to this invention and the similar relationships of a
conventional class-A power amplifier. As shown in FIG. 6, the power amplifier
according to this invention has a higher power-added efficiency than a conventional
class-A power amplifier since as shown in FIG. 5, the gate bias voltage of a
conventional A-class power amplifier is almost constant and the gate bias voltage of the
10 power amplifier of this invention is dependent on the input power. Thus, when the
input power is low, the power amplifier has a low gate bias voltage (close to the
operating range of a conventional class-AB or a class-B amplifier). Conversely, when
the input power is high, the power amplifier has a high gate bias voltage (close to the
operating range of a conventional class-A amplifier). In other words, the power
15 amplifier of this invention is able to provide both high output power and excellent
linearity as a conventional class-A amplifier and to provide a high power-added
efficiency as a conventional class-AB or class-B amplifier.

[0035] FIG. 7 is a circuit diagram of a CMOS power amplifier with an active bias
circuit according to one embodiment of this invention. As shown in FIG. 7, the
20 CMOS power amplifier 700 comprises a transistor 702, an active bias circuit 704 and
other circuits including inductors and capacitors for impedance matching. The
transistor 702 is a major component serving as a power-amplifying transistor in the
power amplifier 700. The active bias circuit 704 is a circuit for providing the
transistor 702 with a gate bias voltage V_{gb1} . The inductors and capacitors together
25 form an impedance matching network.

[0036] Inside the active bias circuit 704, a transistor 712 functions as a diode and
resistors 714, 716 serve to adjust the gate bias voltage and set the basic level of the gate
bias voltage curve as well as provide a cutter for high frequency signals. A depletion

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 transistor 718 functions as a diode and connects serially with a resistor 720. Although the equivalent resistance of the transistor 718 will vary corresponding to the power of the signal, however, the overall effect of the transistor 718 and the resistor 720 is to adjust the basic level of the gate bias voltage because the resistance of the resistor 720 is substantially higher than those of the resistor 714 and 716.

10 [0037] FIG. 8 is a graph showing the relationship of the output current versus the gate bias voltage for two transistor circuits inside the active bias circuit shown in FIG. 7. As shown in FIG. 8, the curves of the output current for the transistor 712 versus the gate bias voltage V_{gb1} is represented by a plurality of curves L1 with a scale labeled on the right vertical axis. Similarly, the curve of the output current for the transistor 718
15 versus the gate bias voltage V_{gb1} is represented by a curve L2 with a scale labeled on the left vertical axis. In FIG. 8, the L1 curves show the output current of the gate bias voltage V_{gb1} for four different input power levels (e.g., input power of -20dBm, -10dBm, 0dBm and 5dBm respectively). It is noted that the gate bias voltage V_{gb1} increases with an increase of the input power. Furthermore, the gate bias voltage V_{gb1}
20 of the cross points of the left curve L2 and the right curves L1 is the gate bias voltage V_{gb1} applied to the power-amplifying transistor 702. Therefore, the gate bias voltage V_{gb1} applied to the transistor 702 increases when the input power is increased.

[0038] FIG. 9 is a graph showing the relationship of a drain-to-source current versus the input power for a power amplifier with an active bias circuit according to this
25 invention and a conventional A-class power amplifier. A conventional A-class power amplifier always has an almost constant gate bias voltage regardless of whether the input power is high or low. Therefore, the effect of input power on the drain-to-source current is minimal. In the power amplifier of this invention, the gate bias voltage is

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

5 low when the input power is low so that the drain-to-source current is small.

Conversely, the gate bias voltage is high when the input power is high so that the drain-to-source current is large. Since power is equal to the product of current and voltage, the power amplifier of this invention has a small DC power consumption and a relatively high power-added efficiency due to a small voltage and current when the input power is low. On the other hand, the power amplifier has a current and voltage similar to a conventional class-A amplifier when the input power is high, therefore, a higher output power and excellent linearity are achieved.

[0039] In another embodiment of this invention, the power amplifier and the active bias circuit may be manufactured by using a system on chip (SOC) process. In an SOC product, the electrical isolations between either active devices or passive devices are very important. Thus, the inductors and transistors are disposed within a deeper N-type doped area to prevent any mutual signal interference.

[0040] Accordingly, the power amplifier of the invention can provides a lower gate bias voltage (close to the operating range of a conventional class-AB or class B power amplifier) when the input power is low, and a higher gate bias voltage (close to the operating range of a conventional class-A power amplifier) when the input power is high. Therefore, the power amplifier of this invention has a high output power and linearity of operation as well as a high power-added efficiency regardless of whether the input power is low or high.

25 [0041] It will be apparent to those skilled in the art that various modifications and variations can be made to the structure of the present invention without departing from the scope or spirit of the invention. In view of the foregoing, it is intended that the

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Clean Version

- 5 present invention cover modifications and variations of this invention provided they fall within the scope of the following claims and their equivalents.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 POWER AMPLIFIER WITH ACTIVE BIAS CIRCUIT

CROSS-REFERENCE TO RELATED APPLICATION

This application claims the priority benefit of Taiwan application serial no.

10 92128662, filed on October 16, 2003.

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] The present invention relates to a power amplifier. More particularly, the
15 present invention relates to a power amplifier with an active bias circuit for improving
power-added efficiency (PAE).

Description of Related Art

[0002] A power amplifier (PA) is an important device in the microwave circuits.
20 For example, a power amplifier is used to amplify the broadcast signals at the
transmission (TX) terminal of a radio frequency circuit. With the popularity of
portable communication systems, a maximum output power and output power
efficiency has have become the critical factors for the development of the wireless
transmission.

25 [0003] The output efficiency of a the power amplifier is represented by the output
power and the output power efficiency. Typically, the maximum output power is the
most important factor in output power while a power gain and power-added efficiency

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 (PAE) are the two most important factors in output power efficiency. The power gain of ~~an~~ the amplifier is defined as ~~the~~ a ratio of the output power ~~and to the~~ an input power. In other words, a larger power gain implies a higher amplifying capacity for the power amplifier. The power-added efficiency is ~~the capacity-an ability of a~~ that the power amplifier ~~to converts~~ a direct current (DC) input power into an alternating current
10 (AC) output power. In fact, power-added efficiency is defined as the ratio of the direct current (DC) input power ~~and to~~ the alternating current (AC) output power, or $PAE = (AC \text{ output power} - DC \text{ input power}) / DC \text{ input power}$. Similarly, the higher the power-added efficiency, the better the power amplifier is. FIG. 1 is a graph showing the relationship of the output power, the power gain and the power-added efficiency
15 versus the input power of a conventional power amplifier. As shown in FIG. 1, most power amplifiers have excellent output power linearity when the input power is small. However, when the input power is large, the output power is no longer linearly amplified and results in a drop in the gain. This drop in the gain is known as a gain compression. The quality of a ~~the~~ power amplifier can be assessed according to the
20 input power at which the gain compression is generated because a later generation of the gain compression means that the power amplifier has better output linearity and maintains a distortion free signal output for a larger input power range.

[0004] FIG. 2 is a circuit diagram of a conventional semiconductor transistor power amplifier. As shown in FIG. 2, the transistor 202 serves as a power amplifier
25 transistor and may be such as a CMOS transistor. In FIG. 2, V_g is the gate bias voltage for the transistor 202; P_{in} is the input power; P_{out} is the output power. In a conventional CMOS power amplifier, a class-A bias design is often adopted. In the

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 class-A bias design, the transistor 202 is biased at a half of the saturation voltage V_{sat} thereof so that a full wave transmission of signal is still possible at a larger output power level. Hence, the power amplifier can have a higher output power and a higher power gain as well as a distortion free linear operating region. However, the a disadvantage is that most A-class power amplifiers are designed to use a single constant
10 gate bias voltage (for example, the gate bias voltage V_g of the transistor 202 is still at half V_{dd}). Since output power is equal to a product of voltage multiplied by and current, power consumption is only reduced by a little at a low output power when the current flow is small and hence leads to an undesirable waste of DC power.

[0005] Therefore, in order to increase output the power efficiency of a the power
15 amplifier, the power amplifier sometimes operates in a class-AB or class-B operating region. In other words, the gate bias voltage V_g of the transistor 202 in FIG. 2 is lowered. Thus, the power-added efficiency (PAE) of the power amplifier is increased. However, the signal waveform is constrained by the gate bias voltage when the output power is large so that the maximum output power and linearity of the power amplifier is
20 are reduced.

[0006] Hence, ~~to enhance~~ enhancing the power-added efficiency and lower direct current power consumption of a the power amplifier without reducing the maximum output power and linearity of operation of the device is important and required.

25 SUMMARY OF THE INVENTION

[0007] Accordingly, at least one objective of the present invention is to provide a power amplifier with an active bias circuit capable ~~for~~ of increasing the power-added

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 efficiency of the amplifier so that a direct current (DC) power consumption is reduced without reducing the a maximum output power or decreasing the linearity of the output power.

[0008] To achieve these and other advantages and in accordance with the purpose of the invention, as embodied and broadly described herein, the invention provides a
10 power amplifier with an active bias circuit. The power amplifier includes a power amplifier transistor and an the active bias circuit. The power amplifier transistor has a the gate connected to a gate bias voltage. The active bias circuit is connected to an input power terminal and the gate of the power amplifier transistor for receiving an input power from the input power terminal and applying a bias voltage to the gate of the
15 power amplifier transistor. Hence, the gate bias voltage will increase in accordance with an increase of the input power.

[0009] In the aforementioned power amplifier, the curve of an increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

[0010] Preferably, the power amplifier transistor and the active bias circuit is
20 manufactured by a system on chip (SOC) process.

[0011] Preferably, the active bias circuit of the aforementioned power amplifier includes a diode and a resistor, and the an equivalent resistance of the diode varies corresponding to the input power.

[0012] This invention also provides an integrated circuit for a power amplifier
25 with an active bias circuit. The integrated circuit includes a power output device, a power amplifier transistor, an active bias circuit and a power input device. The power amplifier transistor has a gate connected to a gate bias voltage. The active bias circuit

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 is connected to the power output device and the gate of the power amplifier transistor for receiving input power from the power output device and applying a bias voltage to the gate of the power amplifier transistor. Hence, the gate bias voltage will increase in accordance with an increase of the input power. The power input device is connected to an output terminal of the power amplifier transistor for receiving the amplified output
10 from the power amplifier transistor.

[0013] In the aforementioned integrated circuit, the curve of the increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

[0014] Preferably, the power amplifier transistor and the active bias circuit is manufactured by a system on chip (SOC) process.

15 [0015] Preferably, the active bias circuit of the aforementioned integrated circuit includes a diode and a resistor, and the equivalent resistance of the diode varies corresponding to the input power.

[0016] This invention also provides a method of providing a gate bias voltage to a transistor power amplifier according to the input power. The method includes
20 providing an input power and then outputting a gate bias voltage corresponding to the input power wherein the gate bias voltage is increased in accordance with the input power.

[0017] In the aforementioned method, the curve of the increase of the gate bias voltage versus the input power is either a linear curve or a non-linear curve.

25 [0018] Accordingly, the power amplifier of the invention can provide a lower gate bias voltage (close to the operating range of a conventional class-AB or class B power amplifier) when the input power is low, and a higher gate bias voltage (close to

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 the operating range of a conventional class-A power amplifier) when the input power is high. Therefore, the power amplifier of this invention has a high output power and linearity of operation as well as a high power-added efficiency regardless of whether the input power is low or high.

[0019] It is to be understood that both the foregoing general description and the
10 following detailed description are exemplary, and are intended to provide further explanation of the invention as claimed.

BRIEF DESCRIPTION OF THE DRAWINGS

[0020] The accompanying drawings are included to provide a further
15 understanding of the invention, and are incorporated in and constitute a part of this specification. The drawings illustrate embodiments of the invention and, together with the description, serve to explain the principles of the invention.

[0021] FIG. 1 is a graph showing the relationships of output power, power gain and power-added efficiency versus input power of a conventional power amplifier.

20 [0022] FIG. 2 is a circuit diagram of a conventional semiconductor transistor power amplifier.

[0023] FIG. 3 is a circuit diagram of a power amplifier with an active bias circuit according to one embodiment of this invention.

[0024] FIG. 4 is a graph showing the relationship of the equivalent resistance
25 versus the input power of a diode.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 [0025] FIG. 5 is a graph showing the relationship of the gate bias voltage versus the input power for a power amplifier with active bias circuit of the invention and a conventional A-class power amplifier.

[0026] FIG. 6 is a graph showing the relationships of output power, power gain and power-added efficiency versus input power for a power amplifier with active bias
10 circuit according to this invention and the similar relationships of a conventional class-A power amplifier.

[0027] FIG. 7 is a circuit diagram of a CMOS power amplifier with an active bias circuit according to one embodiment of this invention.

[0028] FIG. 8 is a graph showing the relationship of the output current versus the
15 gate bias voltage of the two transistor circuits inside the active bias circuit according to one embodiment of this invention.

[0029] FIG. 9 is a graph showing the relationship of the drain-to-source current versus the input power of a power amplifier with an active bias circuit according to this invention and a conventional A-class power amplifier.

20

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0030] Reference will now be made in detail to the present embodiments of the invention, examples of which are illustrated in the accompanying drawings. Wherever possible, the same reference numbers are used in the drawings and the description to
25 refer to the same or like elements.

[0031] FIG. 3 is a circuit diagram of a power amplifier with an active bias circuit according to one embodiment of this invention. As shown in FIG. 3, the power

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 amplifier 300 comprises a transistor 302 and an active bias circuit 304. The transistor 302 serves as a power amplifier transistor such as a CMOS transistor. V_{g1} is a gate bias voltage applied to the transistor 302. P_{in} is an input power and P_{out} is an output power. The active bias circuit 304 further comprises a diode 306 and a resistor 308. FIG. 4 is a graph showing the relationship of the an equivalent resistance versus the
10 input power of a the diode. As shown in FIG. 4, when a signal with a definite power passes through a parallel connected diode, the equivalent resistance of the diode will decrease with an increase in the signal power regardless of whether the diode is set in forward or reverse bias. Hence, if the input power P_{in} of the active bias circuit 304 in FIG. 3 is low, the active bias circuit 304 is equivalent to a voltage divider constructed
15 by a forward bias diode and a serially connected and grounded resistor with high resistance. Thus, by adjusting the resistance of the resistor, the transistor 302 can be operated at a lower gate bias voltage V_{g1} (that is, the gate bias voltage V_{g1} is in the conventional class-AB or class-B operating range). In other words, when the input power P_{in} is low, the power amplifier 300 with the active bias circuit is able to provide a
20 higher power-added efficiency (PAE) so that the DC power consumption is reduced.

[0032] On the other hand, when the input power P_{in} in FIG. 3 is increased, the equivalent resistance of the diode 306 is reduced so that the ~~diode-306~~ voltage
~~difference between~~ across the ~~diode-306~~ resistor 308 is increased. Consequently, with an increase of the input power P_{in} , the gate bias voltage V_{g1} applied to the transistor 302
25 is also increased (that is, the gate bias voltage V_{g1} is in the conventional class-A operating range). In other words, the power amplifier 300 with the active bias circuit

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 is able to provide a higher output power and an excellent linearity of the output power similar to a conventional class-A power amplifier.

[0033] FIG. 5 is a graph showing the relationship of the gate bias voltage V_{g1} applied to the transistor 302 of the power amplifier 300 in FIG. 3 and the gate bias voltage V_g applied to the transistor of a conventional A-class power amplifier versus the
10 input power. As shown in FIG. 5, the conventional A-class power amplifier always has an almost constant gate bias voltage value regardless of whether the input power is high or low. In the power amplifier of this invention, the gate bias voltage value is low when the input power is low and the gate bias voltage value is high when the input power is high.

15 [0034] FIG. 6 is a graph showing the relationship of the output power, power gain and power-added efficiency versus the input power for a the power amplifier with the active bias circuit according to this invention and the similar relationships of a conventional class-A power amplifier. As shown in FIG. 6, the power amplifier according to this invention has a higher power-added efficiency than a conventional
20 class-A power amplifier since as shown in FIG. 5, the gate bias voltage of a conventional A-class power amplifier is almost constant and the gate bias voltage of the power amplifier of this invention is dependent on the input power. Thus, when the input power is low, the power amplifier has a low gate bias voltage (close to the operating range of a conventional class-AB or a class-B amplifier). Conversely, when
25 the input power is high, the power amplifier has a high gate bias voltage (close to the operating range of a conventional class-A amplifier). In other words, the power amplifier of this invention is able to provide both high output power and excellent

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

- 5 linearity as a conventional class-A amplifier and to provide a high power-added efficiency as a conventional class-AB or class-B amplifier.

[0035] FIG. 7 is a circuit diagram of a CMOS power amplifier with an active bias circuit according to one embodiment of this invention. As shown in FIG. 7, the CMOS power amplifier 700 comprises a transistor 702; an active bias circuit 704 and
10 other circuits including inductors and capacitors for impedance matching. The transistor 702 is a major component serving as a power-amplifying transistor in the power amplifier 700. The active bias circuit 704 is a circuit for providing the transistor 702 with a gate bias voltage V_{gb1} . The inductors and capacitors together form an impedance matching network.

15 [0036] Inside the active bias circuit 704, a transistor 712 functions as a diode and ~~transistors~~ resistors 714, 716 serve to adjust the gate bias voltage and set the basic level of the gate bias voltage curve as well as provide a cutter for high frequency signals. A depletion transistor 718 functions as a diode and connects serially with a resistor 720. Although the equivalent resistance of the transistor 718 will vary corresponding to the
20 power of the signal, however, the overall effect of the transistor 718 and the resistor 720 is to adjust the basic level of the gate bias voltage because the resistance of the resistor 720 is substantially higher than those of the resistor 714 and 716.

[0037] FIG. 8 is a graph showing the relationship of the output current versus the gate bias voltage for two transistor circuits inside the active bias circuit shown in FIG. 7.
25 As shown in FIG. 8, the curves of the output current for the transistor 712 versus the gate bias voltage V_{gb1} is represented by a plurality of curves L1 with a scale labeled on the right vertical axis. Similarly, the curve of the output current for the transistor 718

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 versus the gate bias voltage V_{gb1} is represented by a curve L2 with a scale labeled on the left vertical axis. In FIG. 8, the L1 curves show the output current of the gate bias voltage V_{gb1} for four different input power levels (e.g., input power of -20dBm, -10dBm, 0dBm and 5dBm respectively). It is noted that the gate bias voltage V_{gb1} increases with an increase of the input power. Furthermore, the gate bias voltage V_{gb1} of the cross points of the left curve L2 and the right curves L1 is the gate bias voltage V_{gb1} applied to the power-amplifying transistor 702. Therefore, the gate bias voltage V_{gb1} applied to the transistor 702 increases when the input power is increased.

[0038] FIG. 9 is a graph showing the relationship of the a drain-to-source current versus the input power for a power amplifier with an active bias circuit according to this invention and a conventional A-class power amplifier. A conventional A-class power amplifier always has an almost constant gate bias voltage regardless of whether the input power is high or low. Therefore, the effect of input power on the drain-to-source current is minimal. In the power amplifier of this invention, the gate bias voltage is low when the input power is low so that the drain-to-source current is small.

20 Conversely, the gate bias voltage is high when the input power is high so that the drain-to-source current is large. Since power is equal to the product of current and voltage, the power amplifier of this invention has a small DC power consumption and a relatively high power-added efficiency due to a small voltage and current when the input power is low. On the other hand, the power amplifier has a current and voltage

25 similar to a conventional class-A amplifier when the input power is high, therefore, a higher output power and excellent linearity are achieved.

Customer No.: 31561
Application No.: 10/708,371
Docket NO.: 11955-US-PA
Marked Version

5 [0039] In another embodiment of this invention, the power amplifier and the active bias circuit may be manufactured by using a system on chip (SOC) process. In an SOC product, the electrical isolations between either active devices or passive devices are very important. Thus, the inductors and transistors are disposed within a deeper N-type doped area to prevent any mutual signal interference.

10 [0040] Accordingly, the power amplifier of the invention can provides a lower gate bias voltage (close to the operating range of a conventional class-AB or class B power amplifier) when the input power is low, and a higher gate bias voltage (close to the operating range of a conventional class-A power amplifier) when the input power is high. Therefore, the power amplifier of this invention has a high output power and
15 linearity of operation as well as a high power-added efficiency regardless of whether the input power is low or high.

 [0041] It will be apparent to those skilled in the art that various modifications and variations can be made to the structure of the present invention without departing from the scope or spirit of the invention. In view of the foregoing, it is intended that the
20 present invention cover modifications and variations of this invention provided they fall within the scope of the following claims and their equivalents.